Press User Tools

Home	RICOH		Reset	Program Interrupt	Main Power Energy Saver
Copy Copy Scanner Facsimile Communicating Fax Received Printer Printer Printer Printer Printer Printer Printer	Cover Cover Address Book Manaeement	Contraction of the second seco	nt Tech St	ABC 3 DEF ABC 3 DEF AMNO S 8 TUV 9 WXYZ 0 # Sample Copy Start	Login/ Logout Tuser Tools/ Counter (*) Simple Screen (*)
Data In Status	र र		6:00AH		

Press System Settings

🚸 User Tools / Counter / Inquiry			
System Settings	Copier / Document Server Features	ţ	Español
Address Book Mangmnt	Facsimile Features	i	Inquiry
Tray Paper Settings	Printer Features		
Edit Home	Scanner Features		
		B	Maintenance
		123	Counter

Press File Transfer



Press SMTP Server



If you Server name is NOT smtp.sendgrid.net, you are done

If it is smtp.sendgrid.net you need to press change, and replace it with your new SMTP server address

🔹 System Setting	as		Exit
SMTP Server		Cancel	ОК
Select item.			
►Server Name	smtp.sendgrid.net		Change
►Port No.	587 Change Change		
►Use Secure Connection (SSL)	On Off		
		Co	nnection Test

Press change next to the Port No. and enter the correct port number

Select SSL to on or off as required

Press OK

Press SMTP Authentication

🔹 System Settings			Exit	
General Tray Paper Timer Interface File Administrator Settings Settings Settings Transfer Tools				
Delivery Option Not Exist		POP3 / IMAP4 Settings		
		Administrator's E-mail Address	Scanner@copytec	
		E-mail Communication	Port	
SMTP Server	smtp.sendgrid.n	E-mail Reception Interval	1 5 minute(s)	
SMTP Authentication	Cn	Max. Reception E-mail Size	50 MB	
POP before SMTP	Off	E-mail Storage in Server	Off	
Reception Protocol POP3		Default User Name / Password (Send)		
		1 🖊 2 🔺 Pre	vious 🔻 Next	

If SMTP Authentication is required press change next to User Name and enter the user name

Then press change next to E-mail Address and enter the E-mail Address

Press Change next to Password and enter the password in both fields

System Settings			Exit
SMTP Authentication		Cancel	ОК
Select item.			
►SMTP Authentication	On Off		
►User Name	scanner@copytechinc.net		Change
►E-mail Address	scanner@copytechinc.net		Change
▶Password	Change		
►Encryption	Auto On		Off

Press OK

Press Administrator's E-mail Address

🔹 System Settings			Exit	
General Tray Paper Timer Interface File Administrator Settings Settings Settings Transfer Tools				
Delivery Option Not Exist		POP3 / IMAP4 Settings		
		Administrator's E-mail Address	Scanner@copytec	
	L	E-mail Communication	Port	
SMTP Server	smtp.sendgrid.n	E-mail Reception Interval	1 5 minute(s)	
SMTP Authentication	On	Max. Reception E-mail Size	50 MB	
POP before SMTP	Off	E-mail Storage in Server	Off	
Reception Protocol POP3		Default User Name / Password (Send)		
		1 🖊 2 🔺 Pre	vious 🔻 Next	

Press Delete All and enter in the new E-mail Address

Administrator's E-mail Address	Cancel	ОК		
Enter the administrator E-mail address, then press [OK].				
Scanner@copytechinc.net23/128	-> Backspace	Delete All		
<u>`</u> 1 2 3 4 5 6 7 8	9 0 .	- =		
q w e r t y u i o]] 9	1 /		
asd fghjkl	; ,	_		
z x c v b n m ,	. / @			
Shift Lock Shift Space				
Text Entry User Text				